



# Powerware

## Powerware® Automatic Transfer Switch (eATS) for Powerware ePDU™s

Product Focus



### Features

- Dual power inputs automatically select a source best suited to power critical equipment
- Ruggedized relays meet agency spacing requirements for out of phase switching up to 30 amps, while still performing fast enough to minimize transfer time
- Multiple configurations allow selection of options for a variety of mission critical applications

Designed for switching non phase synchronized AC power sources, the automatic transfer switch ePDUs intelligent circuitry monitors both inputs, providing a fast switch transfer from primary to secondary source to power critical equipment without interruption. Status LEDs indicate power available and output source, the ePDU assures the highest level of redundancy to mission critical applications.

## Technical specifications

Part number	Inventory*	Description	Max	Input kW	Function plug	Cord	Orientation	Receptacles	Dimensions W H D
<b>Horizontal mount models</b>									
PWATSSC20001	2	eATS Basic dual C20 inlet 8 C13, 1 C19 recepts	3.33	C20	BA	NA	1U	IEC320-C13 (8), IEC320-C19(1)	1.75 19 7
PWATSS515002	2	eATS Basic dual 5-15 input, 8 5-15 recepts	1.44	5-15P	BA	9'	1U	5-15R(8)	1.75 19 7
PWATSS520003	2	eATS Basic dual 5-20 input, 8 5-20 recepts	1.92	5-20P	BA	9'	1U	5-20R(8)	1.75 19 7
PWATSL520004	2	eATS Basic dual L5-20 input, 8 5-20 recepts	1.92	L5-20P	BA	9'	1U	5-20R(8)	1.75 19 7
PWATSL530005	2	eATS Basic dual L5-30 input, 8 5-20 recepts	2.88	L5-30P	BA	9'	1U	5-20R(8)	1.75 19 9
PWATSL630006	2	eATS Basic dual L6-30 input, 12 C13 recepts	4.99	L6-30P	BA	9'	1U	IEC320-C13(12)	1.75 19 9
PWATSL530007	2	eATS Basic dual L5-30 input, 1 L5-30 recepts	2.88	L5-30P	BA	9'	1U	L5-30R(1)	1.75 19 7
PWATSL630008	2	eATS Basic dual L6-30 input, 1 L6-30 recepts	4.99	L6-30P	BA	9'	1U	L6-30R(1)	1.75 19 7

**\*Inventory Column**

Indicates the stocking priority status. Items categorized as 1 have the highest priority in inventory stocking and replenishment. These are part of the Topseller program and should never be out of stock. Items categorized as 2 and 3 have respectively lower priorities.

UNITED STATES  
8609 Six Forks Road  
Raleigh, NC 27615 U.S.A.  
Toll Free: 1.800.356.5794  
or 919.872.3020

[www.powerware.com](http://www.powerware.com)

CANADA  
Ontario: 416.798.0112  
Toll Free: 1.800.461.9166

LATIN AMERICA  
Argentina: 54.11.4343.6323  
Brazil: 55.11.3616.8500  
México: 52.55.9000.5252

EUROPE/MIDDLE EAST/AFRICA  
Denmark: 45.3686.7910  
Finland: 358.94.52.661  
France: 33.1.6012.7400  
Germany: 49.0.7841.604.0  
Italy: 39.02.66.04.05.40  
Norway: 47.23.03.65.50  
Sweden: 46.8.598.940.00  
United Kingdom: 44.1753.608.700



PowerChain  
Management®

ASIA PACIFIC  
Australia: 61.2.9693.9366  
New Zealand: 64.0.3.343.3314  
China: 86.21.6361.5599  
HK/Korea/Taiwan: 852.2745.6682  
India: 91.11.2649.9414 to 18  
Singapore/SEA: 65.6825.1668

Eaton, Powerware, PowerChain Management and ePDU are trade names, trademarks, and/or service marks of Eaton Corporation or its subsidiaries and affiliates.

© 2008 Eaton Corporation  
All Rights Reserved  
Printed in USA  
PDU14FXA  
March 2008

**EAT•N**

**Powerware**